

# FIREWIRE/USB EXPRESS|34

\* MacBook Pro Requires  
Mac OS X Version 10.5,  
Available October 2007



Part No. FWUSB2-E34

## TECHNICAL SPECIFICATIONS

### Hardware

Warranty	1-year limited warranty
RoHS Compliant	Yes
Bus Interface	ExpressCard/34
Peripherals Supported	Supports all industry standard USB 1.1/2.0 and FireWire 400 peripherals Cables Supported
Cables Supported	6-pin male FireWire 400 cables; USB cables with A-type connector

### FireWire Support

RoHS Compliant	Yes
Number of Ports	2 external
Standard	IEEE 1394A compliant
Data Transfer Rate	100/200/400 Mb/s/sec
Number of Devices Supported	Up to 63 (data only)
Hot Plug	Supports hot-pluggable and hot-swappable device connection

### USB Support

Number of Ports	1 external
Standard	USB Specification v. 1.0/1.1/2.0 compatible. Complies with OHCI (Open Host Controller Interface) and EHCI (Enhanced Host Controller Interface)
Data Transfer Rate	USB 2.0: 480 Mb/s/sec; USB 1.1: 12 Mb/s/sec
Number of Devices Supported	Up to 127
Hot Plug	Supports hot-pluggable and hot-swappable device connection

For MacBook Pro compatibility, this card requires Mac OS X Version 10.5 (Leopard), scheduled for release in October 2007.

## More Ports for Peripherals

Today's notebook computers are small and powerful, but when it comes to connecting accessories, they're limited. They have at least one or two USB ports, and some have a FireWire® port, but most don't have enough places to plug in all your peripherals. Everybody's got gadgets with USB or FireWire connectors—iPod® mobile digital devices, DV camcorders, digital cameras, external drives, printers, keyboards, mice, scanners, to name a few—wouldn't it be nice to plug in more than one at a time? Pop Sonnet's FireWire/USB ExpressCard/34 into your computer's ExpressCard slot to instantly add the USB 2.0 and FireWire 400 ports you need!

Sonnet's FireWire/USB ExpressCard/34 features one USB 2.0 and two FireWire 400 ports, each port offering full-bandwidth data throughput, so there is no performance penalty when you add ports as you add devices. This card works in ExpressCard/34 and ExpressCard/54 slots, and features hot-pluggable and hot-swappable device connection with automatic device configuration.

## Key Benefits

- ▶ Simple way to add more full-bandwidth USB 2.0 and FireWire 400 ports to any compatible computer
- ▶ Plug and play—no drivers to install
- ▶ Supports simultaneous low-, full-, and hi-speed device connections. Maximizes performance for each port
- ▶ Provides fast interface to download videos from your digital camcorder, transfers files to external drives, and more
- ▶ Supports hot-swappable device connection. Plug in and disconnect peripherals without shutting off your computer

## Mac Compatibility

- ▶ MacBook® Pro\*
- ▶ Mac OS X Version 10.5 or later\*

\* For MacBook Pro compatibility, this card requires Mac OS X Version 10.5 (Leopard), scheduled for release in October 2007.

## Windows Compatibility

- ▶ Notebook computer with ExpressCard/34 or ExpressCard/54 slot
- ▶ Windows® XP with SP 2 or later
- ▶ Windows Vista



For  
Windows



RoHS  
COMPLIANT

Sonnet Technologies, Inc.  
8 Autry, Irvine, CA 92618-2708 USA  
Tel: 1-949-587-3500 Fax: 1-949-457-6350  
www.sonnettech.com

